

---

Built-in Antennas Painting Signal Jammer From  
<http://www.jammerbooster.com/>

MODEL:	KJ-12W5
SIZE:	210* 50*170mm
PACKAGE:	Neutral packing

## **Built-in Antennas Painting Mobile Signal Jammer**

**Model: KJ-12w5**

### **Features:**

Remote control available to turn on or off and adjust the output power the Jammer

Output power adjustable of each bands

Hidden design, Jammer looks like a wall painting

Each frequency channel can be controlled separately

5 working Frequency ranges selectable of CDMA, GSM, DCS, PCS, UMTS, WCDMA, LTE, WIFI, 4G WIMAX, GPS, etc

### **Applications:**

Prisons, Recording Studios, Banks, Contract Tendering Rooms, Churches, Classrooms, Testing Facilities, Security Services, Military Units, Secret Services, News Conference Rooms, Libraries, Museums, Courts, Border Patrol and Drug Enforcement, Customs, etc

### **Technical Specifications:**

Total RF Output Power: 12W

---

Jamming frequency bands:

Working Frequency Range	Channel Output Power
CDMA: 851-894MHz	35dBm
GSM: 925-960MHz	35dBm
DCS: 1805-1880MHz	33dBm
PCS: 1900-1990MHz	33dBm
3G: 2110-2170MHz	33dBm

Jamming Range: 2 to 50 meters depending on the environment signal strength

Power Supply: 110V to 240V

Power Adapter Output: 5VDC-6A

Power Consumption: 30W

Working Hours: long time unlimited

Dimension: 550\* 335\*40mm

Net Weight: 3kg

Humidity: 30%-95%

Operating Temp: -10°C - +65°C

Antennas: 5pcs Built-in Directional Antennas

Remote Control: available to on/off and power adjustment of each working band





