
Consumer CDMA&DCS Mobile Signal Booster From
<http://www.jammerbooster.com/>

MODEL:	KR-2365CD
SIZE:	210*160*20mm
PACKAGE:	Neutral packing

23dBm Dual-Band CDMA&DCS Mobile Signal Booster

Model: KR-2365CD

The consumer use Dual-Band CDMA800&DCS1800 Mobile Signal Booster is an effective device that can enlarge the coverage area of the mobile base station and fills in the blind spots in CDMA800MHz and DCS1800MHz mobile network

Product Features

- I Provide quick coverage solution for small signal weak & block zones;
- I Compact size, low consumption, easy installation, great cover;
- I Coverage area up to 500~1000 square meters;
- I High linear design, low interference to BTS;
- I Full duplex and double-end design, external power supply, and convenient installation
- I Provide power indication and uplink and downlink indications.
- I The reliability conforms to GB6993-86 standards.
- I The electromagnetic compatibility conforms to ETS300 609-4 standards.

Technical specifications

Model		KR-2365CD
Frequency range		Uplink: CDMA824-849MHz/ Uplink 1710~1785MHz Downlink: CDMA869-894MHz / Downlink 1805~ 1880MHz 1805~1880MHz
Gain (dB)	Uplink	?55
	Downlink	?60
Output power		?23dBm
Pass band ripple		?8dB
Guard band rejection		?BW-60dB??42MHz ?BW-70dB??45MHz
I/O impedance		50?/N Connector
I/O return loss		?-8dB
Noise figure		?-8dB
Intermodulation attenuation(Po=13dBm)		?-40dBc
Transmission delay		?0.5?s
Working Temperature		-10??50?
Power supply		AC110?220V±10%, 45?55Hz
Size		210*160*20mm
Weight		1.5kg
Reliability		To the GB6993-86 standard
Electromagnetic		To the ETS300 694-4 standard
Indication		a) Power supply LED Indicator b) Export power LED Indicator



