

---

Consumer GSM&DCS Mobile Signal Booster From  
<http://www.jammerbooster.com/>

MODEL:	KR-2365GD
SIZE:	210*160*20mm
PACKAGE:	Neutral packing

## 23dBm Dual-Band GSM&DCS Mobile Signal Booster

Model: KR-2365GD

The consumer use Dual-Band GSM900&DCS1800 Mobile Signal Booster is an effective device that can enlarge the coverage area of the mobile base station and fills in the blind spots in GSM900MHz and DCS1800MHz mobile network

### Product Features

- I Provide quick coverage solution for small signal weak & block zones;
- I Compact size, low consumption, easy installation, great cover;
- I Coverage area up to 500~1000 square meters;
- I High linear design, low interference to BTS;
- I Full duplex and double-end design, external power supply, and convenient installation
- I Provide power indication and uplink and downlink indications.
- I The reliability conforms to GB6993-86 standards.
- I The electromagnetic compatibility conforms to ETS300 609-4 standards.

### Technical specifications

---

**Model****KR-2365GD**

Frequency range

Uplink: GSM 890-915MHz/ Uplink 1710~1785MHz

Downlink: GSM 935-960MHz / Downlink 1805~ 1880MHz 1805~1880MHz

Gain Uplink  
Downlink  
(dB)

?55

?60

Output power

?23dBm

Pass band ripple

?8dB

Guard band rejection

?BW-60dB??42MHz

?BW-70dB??45MHz

I/O impedance

50?/N Connector

I/O return loss

?-8dB

Noise figure

?-8dB

Intermodulation

?-40dBc

attenuation(Po=13dBm)

Transmission delay

?0.5?s

Working Temperature

-10??50?

Power supply

AC110?220V±10%, 45?55Hz

Size

210\*160\*20mm

Weight

1.5kg

Reliability

To the GB6993-86 standard

Electromagnetic

To the ETS300 694-4 standard

Indication

a) Power supply LED Indicator

b) Export power LED Indicator



