

---

Single-Band 3G WCDMA Mobile Signal Booster From  
<http://www.jammerbooster.com/>

MODEL:	KR-2365W/ KR-1765W
SIZE:	210*160*20mm
PACKAGE:	Neutral packing

## Single-Band 3G WCDMA Mobile Signal Booster

Model: KR-1765W /KR-2365W

The consumer use Single-Band 3G WCDMA2100 Mobile Signal Booster is an effective device that can enlarge the coverage area of the mobile base station and fills in the blind spots in 3G WCDMA 2100MHz mobile network

### Product Feature

- IProvide quick coverage solution for small signal weak & block zones;
- ICompact size, low consumption, easy installation, great cover;
- ICoverage area up to 500~1000 square meters;
- IHigh linear design, low interference to BTS;
- IManual Gain control available
- IFull duplex and double-end design, external power supply, and convenient installation
- IProvide power indication and uplink and downlink indications.

The reliability conforms to GB6993-86 standards.

The electromagnetic compatibility conforms to ETS300 609-4 standards.

## Technical specifications

Items		Specifications
Frequency range		Uplink: WCDMA 3G1920-1980MHz Downlink: WCDMA3G2110-2170MHz
Gain (dB)	Uplink	?60
	Downlink	?65
Output power		?23dBm
Pass band ripple		?8dB
Guard band rejection		?BW-60dB??42MHz ?BW-70dB??45MHz
I/O impedance		50?/N Connector
I/O return loss		?-8dB
Noise figure		?-8dB
Intermodulation attenuation(Po=13dBm)		?-40dBc
Transmission delay		?0.5?s
Working Temperature		-10??50?
Power supply		AC110?220V±10%, 45?55Hz
Size		210*160*20mm
Weight		1.5kg
Reliability		To the GB6993-86 standard
Electromagnetic		To the ETS300 694-4 standard
Indication		a) Power supply LED Indicator b) Export power LED Indicator

