

---

Single-Band GSM Mobile Signal Booster From <http://www.jammerbooster.com/>

MODEL:	KR-2365C/G/D/P
SIZE:	210*160*20mm
PACKAGE:	Neutral packing

## Single-Band GSM Mobile Signal Booster

Model: KR-2365C/GD/P

The consumer use Single-Band GSM Mobile Signal Booster is an effective device that can enlarge the coverage area of the mobile base station and fills in the blind spots in GSM mobile network

### Product Feature

IProvide quick coverage solution for small signal weak & block zones;

ICompact size, low consumption, easy installation, great cover;

ICoverage area up to 500~1000 square meters;

IHigh linear design, low interference to BTS;

IManual Gain control available

IFull duplex and double-end design, external power supply, and convenient installation

IProvide power indication and uplink and downlink indications.

IThe reliability conforms to GB6993-86 standards.

The electromagnetic compatibility conforms to ETS300 609-4 standards.

## Technical specifications

Items		Specifications
Frequency range		GSM850/900/1800/1900 (customized)
		GSM850/900/1800/1900 (customized)
Gain (dB)	Uplink	?60
	Downlink	?65
Output power		?23dBm
Pass band ripple		?8dB
Guard band rejection		?BW-60dB??42MHz
		?BW-70dB??45MHz
I/O impedance		50?/N Connector
I/O return loss		?-8dB
Noise figure		?-8dB
Intermodulation attenuation(Po=13dBm)		?-40dBc
Transmission delay		?0.5?s
Working Temperature		-10??50?
Power supply		AC110?220V±10%, 45?55Hz
Size		210*160*20mm
Weight		1.5kg
Reliability		To the GB6993-86 standard
Electromagnetic		To the ETS300 694-4 standard
Indication		a) Power supply LED Indicator
		b) Export power LED Indicator



