

---

8 Bands Built-in Antenna Signal Jammer From  
<http://www.jammerbooster.com/>

MODEL:	KJ-35PW8
SIZE:	400*288*155mm
PACKAGE:	Neutral packing

## 8 Bands Built-in Antenna Waterproof Signal Jammer

**Model: KJ-35PW8**

### **Introductions:**

KJ-35PW8 is Medium Power Built-in Antenna Waterproof Signal Jammer, IP level IP65, can be remote monitored by Internet.

### **Features:**

Output power adjustable

Easy operation and installation

High Efficiency output power, long jamming distance

Effectively making subsections, no interception to base station

---

Waterproof Jammer, proper for outdoor use

Remote monitoring system available

### **Applications:**

Proper for Prison, police, military or government buildings, and any other sensitive locations where the wireless signals are not allowed.

### **Technical Specifications:**

Working frequency bands: 8 bands selectable of VHF, UHF, GSM, DCS, CDMA, WCDMA, TDMA, WIFI 2.4G, WIFI 5.8G, 4G LTE, 4G WIMAX, GPS, etc

Channel output power: up to 5W

Total RF output power: 35W

Internal Modulation: FM Hopping Frequency and Sweeping

Signal source: PLL Synthesized and VCO

Effective jamming range: 50-200m depending on the the environment signal strength;

Power supply: 220VAC/110VAC

Continuous working hours: Long time

Power Consumption: 600W

Antennas type: High Gain Direction Panel Antenna or Omni Antenna

Remote Control: Internet IP monitoring available (optional)

Remote Control Interface: RJ45

Dimension: 400\*288\*155mm

---

Net Weight: 7kgs;

Operating Temp: -20°C - +50°C

Humidity: 5% - 90%









